


Balance 30 Pro



Quick Look

Cellular	Ethernet WAN	Ethernet LAN	Stateful Firewall Throughput	PepVPN Throughput (No Encryption)	PepVPN Throughput (256-bit AES)
1	2 (GE)	4 (GE)	400Mbps	120Mbps	55Mbps

Interfaces

SFP LAN/WAN	No
Wi-Fi AP	Yes
USB	1

Performance

Recommended Users	1-60
Number of PepVPN / SpeedFusion Peers	2/5 ¹
Maximum Number of AP Supported	30

Performance

SpeedFusion Hot Failover	Yes	High Availability	Yes
SpeedFusion WAN Smoothing	Yes [@]	Content Filtering (Lite/Full)	No
SpeedFusion Bandwidth Bonding	Yes [@]	Pepwave AP Series Management	Yes
Remote SIM (used in SIM Injector)	No	Remote AP & Multiple Config Profiles Management	No
Central Management	InControl 2	LAN Bypass	No
Drop In Mode	Yes	Remote User Access	Yes

Core Funtionality

802.1q VLANs Supported	16
Port-Based VLAN	Yes
Load Balancing & Failover	Yes
Load Balancing Algorithms	8
Inbound Load Balancing	No
InControl Cloud Management	Yes

IPsec/L2TP/PPTP VPN Functionality

PepVPN	Yes
IPsec VPN (Network-to-Network)	Yes
Number of IPsec Tunnels	2
L2TP VPN Server	Yes
OpenVPN Server	Yes
PPTP VPN Server	Yes
Maximum PPTP/L2TP/ OpenVPN Users	15
GRE (Network-to-Network)	5

Advanced QoS Functionality

Bandwidth Usage Monitor	Yes
QoS for VoIP and E-Commerce	Yes
User Groups Bandwidth Control	Yes
Web Blocking	Yes

Hardware

LACP (802.3ad) NIC Bonding	No
PoE+ Output	Yes*
Rack-mount	No
Dual Hot Swap Power Supply	No
Power Consumption	28W
Operating Temperature	-40° – 149°F -40° – 65°C

Certifications

FCC, CE, RoHS	Yes
Warranty	1-Year Limited Warranty

[1] PepVPN/SpeedFusion Peers license, it can change the maximum number of PepVPN/SpeedFusion peer.
Balance 30 Pro, PVN-LC-05. Up to 5 PepVPN/SpeedFusion peers.

[@] SpeedFusion Bonding license

Balance 30 Pro, BPL-031-PRO-LC-SF. SpeedFusion Bonding License Key

[*] Requires PoE Activation Kit. Includes power supply and license to enable 802.3af PoE Output Ports.

[1] For a list of supported modems, please refer to <https://www.peplink.com/technology/4g3g-modem-support/>.

[2] Recommendation for sizing purposes only. No software restrictions applied.

[3] Router Throughput and PepVPN/SpeedFusion Throughput is based on Ethernet frame sizes of 1280 or 1518 bytes. Actual performance can vary across different networking environments. Figures apply to the latest hardware revision. The throughput result is tested with DHCP/Static IP.

[4] The number of peer Peplink or Pepwave devices you can connect using SpeedFusion VPN.

[5] IPsec only supports connection with Cisco, Juniper, Peplink or Pepwave devices.

Balance 20/30 LTE/One/210/310 comes with AP Controller Standard, which supports up to two configuration profiles with multiple SSIDs, meaning that all APs will

[6] share the same configuration, and you can only manage APs on the local physical LAN. 305/310 5G/310 5G Fiber/380/380X/580/580X/710/1350/2500/SDX/SDX